



Siemens Gigaset C470 IP

Gigaset C470IP

Pro nastavení Vašeho FAYN účtu klikněte na položky dle níže uvedeného pořadí.

1. Settings

Home Settings Status Log Off ?

2. Connections

IP Configuration
Telephony
Audio
Number Assignment
Call Forwarding
Dialling Plans
Network Mailbox
Advanced Settings
Messaging
Services
Handsets
Miscellaneous

IP Connection

	Name / Provider	Suffix	Status	3. Edit	Active
1.	IP1 Other Provider	#1	Registered	Edit	<input checked="" type="checkbox"/>
2.	IP2 Other Provider	#2	Disabled	Edit	<input type="checkbox"/>
3.	IP3 Other Provider	#3	Disabled	Edit	<input type="checkbox"/>
4.	IP4 Other Provider	#4	Disabled	Edit	<input type="checkbox"/>
5.	IP5 Other Provider	#5	Disabled	Edit	<input type="checkbox"/>
6.	IP6 Other Provider	#6	Disabled	Edit	<input type="checkbox"/>

Gigaset.net

Name	Suffix	Status	Active
Gigaset.net	#9	Registered	<input checked="" type="checkbox"/>

Fixed Line Connection

Name	Suffix	Edit
Fixed Line	#0	Edit

SIEMENS



Gigaset C470IP

Home Settings Status Log Off

IP Configuration

Telephony

Connections

Audio

Number Assignment

Call Forwarding

Dialling Plans

Network Mailbox

Advanced Settings

Messaging

Services

Handsets

Miscellaneous

1. IP Connection

You can replace the default name with a name or the actual phone number to distinguish this connection.

Connection Name or Number:

Auto Configuration

If your provider has issued you with a configuration code, you can use it to start the automatic connection configuration here.

Auto Configuration Code:

Provider: Other Provider

Personal Provider Data

Authentication Name:

Authentication password:

Username:

Display name:

4.

Klikněte na tlačítko "Show Advanced Settings" pro zobrazení tabulky, kde vyplníte své FAYN údaje.

SIEMENS

Personal Provider Data

Authentication Name:	<input type="text" value="Vaše FAYN tel. číslo (bez 420)"/>
Authentication password:	<input type="text" value="Vaše SIP heslo"/>
Username:	<input type="text" value="Vaše FAYN tel. číslo (bez 420)"/>
Display name:	<input type="text" value="Vaše FAYN tel. číslo (bez 420)"/>
<input type="button" value="Hide Advanced Settings"/>	
General Provider Data	
Domain:	<input type="text" value="fayn.cz"/>
Proxy server address:	<input type="text" value="sip.fayn.cz"/>
Proxy server port:	<input type="text" value="5060"/>
Registrar server:	<input type="text" value="sip.fayn.cz"/>

Vyplňte všechna uvedená políčka podle údajů, které vidíte na této stránce a nastavení potvrďte tlačítkem "Set".

5.

Registrar server port:	<input type="text" value="5060"/>
Registration refresh time:	<input type="text" value="180"/> sec
Network	
STUN enabled:	<input type="radio"/> Yes <input checked="" type="radio"/> No
STUN server:	<input type="text"/>
STUN port:	<input type="text" value="3478"/>
STUN refresh time:	<input type="text" value="240"/> sec
NAT refresh time:	<input type="text" value="20"/> sec
Outbound proxy mode:	<input type="radio"/> Always <input checked="" type="radio"/> Auto <input type="radio"/> Never
Outbound proxy:	<input type="text"/>
Outbound proxy port:	<input type="text" value="5060"/>

6.

<input type="button" value="Set"/>	<input type="button" value="Cancel"/>	<input type="button" value="Delete"/>
------------------------------------	---------------------------------------	---------------------------------------

SIEMENS